

**Conversion table - American Wire Gauge - mm. - mm<sup>2</sup>**

AWG N°	Diam. mm.	Area mm <sup>2</sup>		AWG N°	Diam. mm.	Area mm <sup>2</sup>
1	7,350	42,400		16	1,290	1,3100
2	6,540	33,600		17	1,150	1,0400
3	5,830	26,700		18	1,024	0,8230
4	5,190	21,200		19	0,912	0,6530
5	4,620	16,800		20	0,812	0,5190
6	4,110	13,300		21	0,723	0,4120
7	3,670	10,600		22	0,644	0,3250
8	3,260	8,350		23	0,573	0,2590
9	2,910	6,620		24	0,511	0,2050
10	2,590	5,270		25	0,455	0,1630
11	2,300	4,150		26	0,405	0,1280
12	2,050	3,310		27	0,361	0,1020
13	1,830	2,630		28	0,321	0,0804
14	1,630	2,080		29	0,286	0,0646
15	1,450	1,650		30	0,255	0,0503

**M&W IGNITIONS**